







## **OCTAVIO<sup>®</sup> FUZZ**

This pedal provides the classic "octave up" effect that Jimi Hendrix<sup>™</sup> utilized so potently on tracks such as "One Rainy Wish" and "Purple Haze," featuring colorful, iconic art from legendary rock artist Gered Mankowitz.

## DIRECTIONS

- Run a cable from your guitar to the JHM6's INPUT jack and run another cable from the JHM6's OUTPUT jack to your amplifier.
- Start with LEVEL and FUZZ controls at 12 o'clock.
- Turn the effect on by depressing the footswitch.
- Rotate LEVEL knob clockwise to increase overall volume or counterclockwise to decrease it.
- Rotate FUZZ knob clockwise to increase amount of fuzz or counterclockwise to decrease it.

## POWER

The Jimi Hendrix<sup>™</sup> Octavio Fuzz can be powered by one 9-volt battery (remove bottom plate to install), an adapter such as the ECB003, or the MXR DC Brick<sup>™</sup> and Iso-Brick<sup>™</sup> power supplies.

## SPECIFICATIONS

| input impedance    |               |
|--------------------|---------------|
| Max Fuzz           | ~20kΩ @ 1kHz  |
| Min Fuzz           | ~370kΩ @ 1kHz |
| Max Input          | -6dBv         |
| Output Impedance   |               |
| Max Volume         | 1.5kΩ         |
| Mid Volume         | 50kΩ          |
| Max Output         | 1.7 Vpp       |
| Gain Range         | 8dB to 37dB   |
| Bypass             | True Hardwire |
| Current Draw       | 5.9mA         |
| Power Requirements | 9 volts DC    |

\*Drive stage adjusted maximum CW \*\*With all controls at mid position



DUNLOP MANUFACTURING, INC. P.O. BOX 846 BENICIA, CA 94510 U.S.A. TEL: 1-707-745-2722 FAX: 1-707-745-2658